



The 8-button transmitter FRT-HS 8 is a handheld unit for RF transmission of up to 8 commands, which can be received and indicated visually and/or by tone or which can switch up to 8 relays. The 8 buttons can either be imprinted with „F1“ ... „F8“ or can be blank, having two detachable strips for an individual inscription.

The handheld unit contains a RF-transceiver for SRD-Band 869 MHz for licence free operation within the EU, a control-LED to indicate both, the transmission activity and the technical call acknowledgement by the receiving unit. In case that this should fail, one or even a second call repetition is initiated automatically.

A rotary switch inside the battery compartment is used for setting the address of the 8-button transmitter, being preset to “1”. For use of multiple transmitters in the same premise, it can be set to “1” ... “9”, enabling the individual receiver unit (pager or call indication panel) to recognize, which particular transmitter had sent the call. When set to “0” the transmitter behaves like 8 single individual call buttons.

Technical data:

Dimensions: ca. L105 x B58 x H19mm
Protection class: IP 40, ABS
Weight: ca. 50g
Power supply: battery 2 x 1,5V, Type AAA, Alkali-Mangan

Options:

Clip to be screwed at the back
Holder for wall mounting of the transmitter with clip

Selection of matching receivers:

FRT-RX-2	Receiver for 2 commands, each with 1 relay
FE-8 RG	Receiver unit with 8 relays
FRT-8 N	Receiver unit with numeric display (1 ... 8)
FRT-64R Touch	Call indication touch panel (1 ... 16/32/64)
MP-U3	Mobile wrist watch pager with vibration and alphanumeric LCD
MP-T3	Mobile pocket pager with vibration, tone and alphanumeric LCD